

Ethernet Cable Kit for UDC 2500/3200/3500

Document Number: 51-52-33-143

Effective: 2/07

Supersedes: 8/13/04

Summary

This kit lets you connect an Ethernet cable from your UDC controller to a hub or PC.

Contents

1 Ethernet RJ45 Cable, 2 Tie Wraps

Table 1 UDC2500 or UDC3200 procedure



Step	Action																														
1	<div></div> <p>Figure 1 UDC2500/3200 terminal connections</p> <p>If you have:</p> <ul style="list-style-type: none">MDI-compliant hub with straight-through cable orPC with crossover cable <p>then make these connections:</p> <table><thead><tr><th><u>UDC Terminal</u></th><th><u>UDC Signal Name</u></th><th><u>Wire Color</u></th><th><u>RJ45 Socket Pin #</u></th><th><u>Hub/PC Signal Name</u></th></tr></thead><tbody><tr><td>Position 14</td><td>Shield</td><td>Black/Bare</td><td>Shield</td><td>Shield</td></tr><tr><td>Position 15</td><td>RX-</td><td>Orange</td><td>6</td><td>TX-</td></tr><tr><td>Position 16</td><td>RX+</td><td>White/Orange</td><td>3</td><td>TX+</td></tr><tr><td>Position 17</td><td>TX-</td><td>Brown</td><td>2</td><td>RX-</td></tr><tr><td>Position 18</td><td>TX+</td><td>White/Brown</td><td>1</td><td>RX+</td></tr></tbody></table>	<u>UDC Terminal</u>	<u>UDC Signal Name</u>	<u>Wire Color</u>	<u>RJ45 Socket Pin #</u>	<u>Hub/PC Signal Name</u>	Position 14	Shield	Black/Bare	Shield	Shield	Position 15	RX-	Orange	6	TX-	Position 16	RX+	White/Orange	3	TX+	Position 17	TX-	Brown	2	RX-	Position 18	TX+	White/Brown	1	RX+
<u>UDC Terminal</u>	<u>UDC Signal Name</u>	<u>Wire Color</u>	<u>RJ45 Socket Pin #</u>	<u>Hub/PC Signal Name</u>																											
Position 14	Shield	Black/Bare	Shield	Shield																											
Position 15	RX-	Orange	6	TX-																											
Position 16	RX+	White/Orange	3	TX+																											
Position 17	TX-	Brown	2	RX-																											
Position 18	TX+	White/Brown	1	RX+																											
2	<p>If you have PC with straight-through cable then make these connections:</p> <table><thead><tr><th><u>UDC Terminal</u></th><th><u>UDC Signal Name</u></th><th><u>Wire Color</u></th><th><u>RJ45 Socket Pin #</u></th><th><u>PC Signal Name</u></th></tr></thead><tbody><tr><td>Position 14</td><td>Shield</td><td>Black/Bare</td><td>Shield</td><td>Shield</td></tr><tr><td>Position 15</td><td>RX-</td><td>Brown</td><td>2</td><td>TX-</td></tr><tr><td>Position 16</td><td>RX+</td><td>White/Brown</td><td>1</td><td>TX+</td></tr><tr><td>Position 17</td><td>TX-</td><td>Orange</td><td>6</td><td>RX-</td></tr><tr><td>Position 18</td><td>TX+</td><td>White/Orange</td><td>3</td><td>RX+</td></tr></tbody></table>	<u>UDC Terminal</u>	<u>UDC Signal Name</u>	<u>Wire Color</u>	<u>RJ45 Socket Pin #</u>	<u>PC Signal Name</u>	Position 14	Shield	Black/Bare	Shield	Shield	Position 15	RX-	Brown	2	TX-	Position 16	RX+	White/Brown	1	TX+	Position 17	TX-	Orange	6	RX-	Position 18	TX+	White/Orange	3	RX+
<u>UDC Terminal</u>	<u>UDC Signal Name</u>	<u>Wire Color</u>	<u>RJ45 Socket Pin #</u>	<u>PC Signal Name</u>																											
Position 14	Shield	Black/Bare	Shield	Shield																											
Position 15	RX-	Brown	2	TX-																											
Position 16	RX+	White/Brown	1	TX+																											
Position 17	TX-	Orange	6	RX-																											
Position 18	TX+	White/Orange	3	RX+																											
3	Secure cable to controller by attaching tie wraps through the holes in the controller flange.																														

Table 2 UDC3500 procedure

Step	Action																														
1	<div><p>Figure 2 UDC3500 terminal connections</p><p>If you have:</p><p>MDI-compliant hub with straight-through cable or</p><p>PC with crossover cable</p><p>then make these connections:</p><table><thead><tr><th>UDC Terminal</th><th>UDC Signal Name</th><th>Wire Color</th><th>RJ45 Socket Pin #</th><th>Hub/PC Signal Name</th></tr></thead><tbody><tr><td>Position 4</td><td>Shield</td><td>Black/Bare</td><td>Shield</td><td>Shield</td></tr><tr><td>Position 24</td><td>RX-</td><td>Orange</td><td>6</td><td>TX-</td></tr><tr><td>Position 25</td><td>RX+</td><td>White/Orange</td><td>3</td><td>TX+</td></tr><tr><td>Position 26</td><td>TX-</td><td>Brown</td><td>2</td><td>RX-</td></tr><tr><td>Position 27</td><td>TX+</td><td>White/Brown</td><td>1</td><td>RX+</td></tr></tbody></table></div>	UDC Terminal	UDC Signal Name	Wire Color	RJ45 Socket Pin #	Hub/PC Signal Name	Position 4	Shield	Black/Bare	Shield	Shield	Position 24	RX-	Orange	6	TX-	Position 25	RX+	White/Orange	3	TX+	Position 26	TX-	Brown	2	RX-	Position 27	TX+	White/Brown	1	RX+
UDC Terminal	UDC Signal Name	Wire Color	RJ45 Socket Pin #	Hub/PC Signal Name																											
Position 4	Shield	Black/Bare	Shield	Shield																											
Position 24	RX-	Orange	6	TX-																											
Position 25	RX+	White/Orange	3	TX+																											
Position 26	TX-	Brown	2	RX-																											
Position 27	TX+	White/Brown	1	RX+																											
2	<p>If you have PC with straight-through cable then make these connections:</p> <table><thead><tr><th>UDC Terminal</th><th>UDC Signal Name</th><th>Wire Color</th><th>RJ45 Socket Pin #</th><th>PC Signal Name</th></tr></thead><tbody><tr><td>Position 4</td><td>Shield</td><td>Black/Bare</td><td>Shield</td><td>Shield</td></tr><tr><td>Position 24</td><td>RX-</td><td>Brown</td><td>2</td><td>TX-</td></tr><tr><td>Position 25</td><td>RX+</td><td>White/Brown</td><td>1</td><td>TX+</td></tr><tr><td>Position 26</td><td>TX-</td><td>Orange</td><td>6</td><td>RX-</td></tr><tr><td>Position 27</td><td>TX+</td><td>White/Orange</td><td>3</td><td>RX+</td></tr></tbody></table>	UDC Terminal	UDC Signal Name	Wire Color	RJ45 Socket Pin #	PC Signal Name	Position 4	Shield	Black/Bare	Shield	Shield	Position 24	RX-	Brown	2	TX-	Position 25	RX+	White/Brown	1	TX+	Position 26	TX-	Orange	6	RX-	Position 27	TX+	White/Orange	3	RX+
UDC Terminal	UDC Signal Name	Wire Color	RJ45 Socket Pin #	PC Signal Name																											
Position 4	Shield	Black/Bare	Shield	Shield																											
Position 24	RX-	Brown	2	TX-																											
Position 25	RX+	White/Brown	1	TX+																											
Position 26	TX-	Orange	6	RX-																											
Position 27	TX+	White/Orange	3	RX+																											
3	Secure cable to controller by attaching tie wraps through the holes in the controller flange.																														

Warranty/Remedy

Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship. Contact your local sales office for warranty information. If warranted goods are returned to Honeywell during the period of coverage, Honeywell will repair or replace without charge those items it finds defective. The foregoing is Buyer's sole remedy and is **in lieu of all other warranties, expressed or implied, including those of merchantability and fitness for a particular purpose**. Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this printing. However, we assume no responsibility for its use.

While we provide application assistance personally, through our literature and the Honeywell web site, it is up to the customer to determine the suitability of the product in the application